

PSE Conformance Test Suite

December 6 2019 7:04 PM
Port Count: 6
Loop Count: 1
PSE Tested: Sample Type-3 2-Event PSE

Sifos Technologies logo and report information including Test Mode: 30 Watt PHY, Sifos Interop Index: 100%, Error Log: None, version 5.1.00, report version 5.1.00

Main test results table with columns for test category, PSA-3000 ports (1-1 to 3-3), UNITS, Min, Max, Average, Low Limit, P/F, High Limit, P/F. Tests include det.v, det.i, det.range, det.time, det.resource, class.v, class.time, pwrup.time, pwrup.inrush, pwrcon.v, pwrcon.pwrcep, pwrcon.maxi, pwrcon.overlid, pwrcon.overid, smps.dc.valid, smps.dc.pwrcep, smps.dc.overlid, pwrcon.w, pwrcon.v, pwrcon.overlid, smps.dc.valid, smps.dc.pwrcep, smps.dc.overlid, pwrcon.w, pwrcon.v, pwrcon.overlid, smps.dc.valid, smps.dc.pwrcep, smps.dc.overlid.